Product data sheet Characteristics

QO2020CP

QO Tandem Mini Circuit Breaker 20/20A 1P 120/240V 10kA Plug-in Mount

Product availability: Stock - Normally stocked in distribution facility







Main

| Product or component type | Miniature circuit-breaker | |
|-----------------------------|---------------------------|---|
| Range of product | QO | |
| Line Rated Current | 20 A | |
| System Voltage | 120/240 V AC | |
| Mounting mode | Plug-in | |
| Poles description | 1P | |
| Circuit breaker type | Tandem | |
| Circuit breaker application | HACR rated | : |
| Electrical connection | Box lugs | : |
| Type of packing | Consumer packaging | |
| | | |

Complementary

| Breaking capacity | 10 kA at: 120/240 V AC | |
|---------------------------|-----------------------------------|---------------|
| Number of spaces required | 1 | |
| AWG gauge | AWG 14AWG 8 (copper or aluminium) | |
| Height | 3.22 in | ilite |
| Depth | 2.91 in | allo State |
| Width | 0.75 in | |
| | | |

Environment

| Littiioiiii | | ğ |
|---------------------------------------|----------------|---|
| Product certifications | UL listed | |
| | CSA | , |
| Ambient air temperature for operation | 104 °F (40 °C) | |

Ordering and shipping details

| oracing and compping actume | | |
|-----------------------------|--------------------------------|--|
| Category | 01329 - QO TANDEMS BULK BRKRS. | |

| Discount Schedule | CPQ | |
|-----------------------|----------------|--|
| GTIN | 00047569008986 | |
| Nbr. of units in pkg. | 10 | |
| Package weight(Lbs) | 0.31 | |
| Returnability | Υ | |
| Country of origin | MX | |

Offer Sustainability

| Sustainable offer status | Green Premium product | |
|----------------------------------|---|--|
| RoHS (date code: YYWW) | Compliant - since 1323 - Schneider Electric declaration of conformity | |
| | Schneider Electric declaration of conformity | |
| REACh | Reference not containing SVHC above the threshold | |
| | Reference not containing SVHC above the threshold | |
| Product environmental profile | Available | |
| Product end of life instructions | Need no specific recycling operations | |